

# AC1200 Wireless Dual Band USB Adapter

# **WF2190**

#### Features

- Maximum speed up to 2.4GHz 300Mbps and 5GHz 867Mbps.
- ➤ Integrate the latest 802.11 AC technology, use in 2.4 G or 5 G Networks.
- ➤ 2\*5dBi detachable antennas allowing for stronger antenna upgrades.
- Advanced security feature with the latest WPA2 encryption to protect the network.
- Easy connection to a wireless network at a push of the WPS button.
- Access Point feature to set up a Wi-Fi hotspot to share the Internet.
- Easy to install and configure with the setup CD and utility.





### Description

The netis WF2190 is designed to connect a desktop or notebook computer to a wireless network and access high-speed Internet connection. It's compatible with 802.11a/b/g/n/ac devices and provides the wireless transfer speed up to 2.4GHz 300Mbps and 5GHz 867Mbps, offering a better performance on online gaming, HD video streaming, and VoIP phone calling. With the 802.11n MIMO and 802.11ac technology, it ensures a strong and stable wireless connection and allows you to enjoy the wireless freedom around your home. Moreover, it features with a WPS button which helps you easily setup a secure wireless connection in a snap.

#### Specification

Wireless	
Standards	IEEE 802.11b/ a/g/n/ac
Signal Rate	2.4GHz Up to 300Mbps
	5 GHz UP to 867Mbps
Frequency Range	2.4-2.4835GHz;5.180-5.825GHZ
Modes	Station, Access Point,
Wireless Security	Support 64/128-bit WEP, WPA-PSK/WPA2-PSK

Hardware	
Port	USB 3.0
Button	WPS
Dimensions (L x W x H )	92.5 x 27 x 15 mm

Others	
Certification	FCC, CE,KC
System Requirements	Windows XP/Vista/7/8/8.1/10, MAC OS, Linux
Environment	Operating Temperature: 0°C~40°C
	Storage Temperature: -40°C ~70°C
	Operating Humidity: 10%~90% non-condensing
	Storage Humidity: 5%~90% non-condensing
Package	1 * WF2190
	1 * Quick Installation Guide
	1 * Driver CD



# Diagram



Specifications are subject to change without notice. Netis is a registered trademark of Netis Systems Co., Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. No part of the specifications may be reproduced in any form or by any means or used to make any derivative such as translation, transformation, or adaptation without permission from Netis Systems Co., Ltd.

