



The **KVM-AS-41DA** is a 4-Port KVM-Switch with reasonable price and automatic audio switch for Desktops

The KVM is connected to your system via USB (Keyboard / Mouse), 4x 3.5mm Audio Jack (Audio Mic/Line) and DVI-I or DVI-D by 4 included cables.

Specifications

Outputs	4
Connectors input	4x DVI-I or DVI-D (VGA, USB Keyboard, Mouse (only digital)) 8x 3.5mm 3 Pol. Audio Jack (4x Line in/4x Mic in) 1x Power
Connectors output	2x USB (Keyboard/Mouse) 2x 3.5mm 3 Pol. Audio Jack (1x Line out/1x Mic out) 1x DVI-I or DVI-D (only digital)
Controls	4x selection
LED	4x selection, 4x online
Supported operating system	No Restrictions
Switch Modi	Hotkey oder Controls
Switch Scan-Time	5s (fix)
DDC	•
Display Resolution	1920x1200 DVI Single Link
Power	Via connected PC or External PSU (optional)
Input	9V/0,5A
Material	Rust-resistant Steel
Operating Temperature	5°C~40°C
Storage Temperature	-2°C~60°C
Humidity	0-80%
MBTF	Average 120000Std.
Netto-Dimensions (H/W/D)	41x203x115mm
Package-Dimensions (H/W/D)	100x275x210mm
Weight netto	0.76Kgs
Weight gross	2.01Kgs
Packing Units	Shipping Unit: 1 piece
Guarantee and Warranty	24 Month Warranty
Article Number	88887201
EAN-Code	4260133128842
Scope of Delivery	4x Cable DVI-I/USB/Audio to DVI-I/USB/Audio (180cm) User manual on CD
Features	4x Hotkeys

- = existent
- = non existent