No warmen to the sound department of the information Ctate 00 DC 00 114

Starter 4 Midi 500W







Starter 4 – Thanks to its clear design this slim and modern Midi-tower is the perfect choice for offices and schools. The blue illuminated power button fits perfectly into the design and bestows it with something special.

Besides the optical amenity the **Starter 4** convinces with a super silent 500W power supply with 12cm fan, 3 fan mounts, side panels attached with thumbscrews and a sturdy finish exterior and interior.

The controls and front connectors are all conveniently situated in the middle of the front panel. HD-Audio/AC-97, 1x USB 2.0 and 1x USB 3.0 front connectors rounds off the positive image.



Starter 4 Midi 500W

<u>pecifications</u>	
Motherboard	ATX, μATX
Drive Bays	5.25" external: 4 3.5" external: 1 3.5" internal: 5/3* 2.5" internal: 0/1*
Front Connectors	USB 2.0: 1 USB 3.0: 1 Microphone: 1 Headphone: 1
Cooling System	Rear: 1x 80, 92 or 120mm Side: 2x 80, 92 or 120mm
Packing Units	Shipping Unit: 1 Piece Pallet: 28 Pieces
Guarantee and Warranty	Case 24 Months Warranty PSU 24 Months Guarantee
Article Number EAN-Code	88881082 4260133121874
Scope of Delivery	Power Cord Screw Set Speaker
Features	500W Power supply Reset buttor Blue illuminated LED power buttor Side panels attached with thumbscrews USB and audio connectors as block connector HD Audio/AC-97 compatible
	*When using one 2.5" hard drive, it is not possible to install two 3.5" hard drive.

Dimensions and Weight

	Cage	Case	Package		
Height	410mm	415mm	495mm		
Width	185mm	185mm	230mm		
Depth	400mm	440mm	475mm		
Weight (net): 4.84Kg Weight (gross): 5.6Kg					

Power	Su	ply
	_	

Connector	Quantity	Max. Length
Mainboard 20+4Pin	1x	41cm
P4 12V 4Pin	1x	43cm
P4/EPS 4+4Pin	-	-
P8 12V 8Pin	-	-
PCI-Express 6+2Pin	-	-
PCI-Express 6Pin	-	-
IDE 4Pin	2x	58cm
S-ATA	3x	73cm
Floppy	1x	73cm
RPM sensor cable	-	-
Fan Control	-	-
Fan: 120mm	1x	-

